



ISDS210A  
ISDS210B

# ISDS210A(B) User Guide

InstruStar Electronic Technology

2015-8-20



ISDS210A  
ISDS210B

## contents

<b>1.Introduction.....</b>	<b>1</b>
<b>2.Feature Description.....</b>	<b>1</b>
<b>3.Software Installation.....</b>	<b>2</b>
<b>4.Oscilloscope / Spectrum analyzer/DDS.....</b>	<b>2</b>



ISDS210A  
ISDS210B

## PC SYSTEM REQUIREMENTS

- Windows XP, Win7, Win8, Win10
- Pentium or higher processor
- USB2.0 High speed port.
- 512MB RAM
- 1GB hard disk space

## 1.Introduction

ISDS210A/ISDS210B dual-channel digital oscilloscope, with "low-cost, high-performance" as the design goals. well-designed bandwidth of 40M, 100M sampling rate, 2 channels, alternating support X-T and X-Y alternating pattern of two-channel virtual oscilloscope, spectrum analyzer. Meanwhile, ISDS210B has DDS function. DDS support 5 kinds of waveform output, Sine wave can output up to 20M. The device communicate with the PC via high speed USB2.0.

	Digital oscilloscope	Spectrum analyzers	DDS
ISDS210A	√	√	
ISDS210B	√	√	√

## 2.Feature Description

Digital oscilloscope	
<b>Channels</b>	2
<b>Impedance</b>	1MΩ 25pF
<b>Coupling</b>	AC/DC
<b>Vertical resolution</b>	8Bit
<b>Gain range</b>	-16V ~ 16V (probe X1) -160V ~ 160V (probe X10)
<b>Vertical accuracy</b>	±3%
<b>Timebase range</b>	1ns-20s
<b>Input Protection</b>	Diode, 50Vpk
<b>Autoset</b>	Yes(10Hz to 40MHz)
<b>Trigger Mode</b>	Auto、Normal and Signal
<b>Trigger Type</b>	No、Rising edge、Falling edge、 Rising edge or Falling edge
<b>Trigger level</b>	Yes
<b>Trigger Source</b>	CH1, CH2
<b>Buffer Size</b>	256KB/CH
<b>Bandwidth</b>	40MHz
<b>Max sample</b>	100MS/s
<b>Vertical mode</b>	CH1, CH2, ADD, SUB, MUL
<b>Display Mode</b>	X、Y-T 和 X-Y
<b>measurements</b>	Yes
<b>Wave save</b>	Osc(Private)、Excel and Bmp

Spectrum analyzers	
<b>Channels</b>	2
<b>Bandwidth</b>	40MHz
<b>Algorithm</b>	FFT(18 windows)、correlation
<b>FFT points</b>	8-1048576/CHN
<b>FFT measure</b>	Harmonic(1-7)、SNR、SINAD、ENOB、THD、SFDR
<b>Filter processing</b>	FIR filter supports arbitrary range of frequency sampling method , and Rectangle, bartlett, triangular, cosine, hanning, bartlett_hanning, hamming, blackman, blackman_Harris, tukey, Nuttall, FlatTop, Bohman, Parzen, Lanczos, kaiser, gaussand dolph_chebyshev, window method design. IIR filter support "Butterworth", "Chebyshev I", "Chebyshev II", "Elliptic" type of filter design

DDS(Only ISDS210B)	
<b>Wave</b>	Sine, Square(Duty circle variable),Triangle,Up Sawtooth,Down Sawtooth
<b>Amplitude</b>	$\geq 9\text{Vp-p}$ (no load)
<b>Impedance</b>	$200\Omega \pm 10\%$
<b>Offset</b>	$\pm 2.5\text{V}$
<b>Frequency range</b>	1Hz ~ 20MHz(Sine), 1Hz ~ 2MHz(Others)
<b>Frequency resolution</b>	1Hz
<b>Frequency steadiness</b>	$\pm 1 \times 10^{-3}$
<b>Frequency precision</b>	$\pm 5 \times 10^{-3}$
<b>Triangular wave linearity</b>	$\geq 98\%$ (1Hz~10kHz)
<b>Sine wave distortion</b>	$\leq 0.8\%$ (1kHz)
<b>Square wave rising/falling time</b>	$\leq 100\text{ns}$
<b>Square wave duty circle</b>	1%~99%
<b>SWEEP</b>	
<b>Sweep range</b>	Fs 到 Fe
<b>Sweep time range</b>	0.1 ~10 s
<b>Amplitude</b>	0.5Vp-p ~ 10Vp-p

**Note: The oscilloscope factory calibration, if you are not satisfied with the measurements, can manual calibration, the specific reference oscilloscope instructions.**

### 3. Software Installation

Please refer to the "Software and Driver Installation.pdf".



ISDS210A  
ISDS210B

#### 4.Oscilloscope / Spectrum analyzer /DDS

Please refer to the "Multi VirAnalyzer User Guide.pdf", "Digital storage oscilloscope (Professional Version).pdf" and "Digital storage oscilloscope (Simplified Version).pdf".